

## "QUICKDISC+" CARTRIDGE

The Quickdisc+ cartridge provides load and save facilities that are 5 - 7 times faster than normal, abbreviated disk commands which are summarised later, and the following utilities: 20 second Format; 3 minute Disk Backup (Unprotected Disk Only); Selective fast file copier; Centronics Interface (user port) and a reset switch which is unstoppable (as far as we know).

All utilities will operate with a Commodore printer connected and with either Disc Drive device numbers.

The cartridge does not affect user memory in any way by using advanced cartridge switching techniques developed on the Isle of Wight.

After the centron command, output f normal using the 255), D = Device (miss out). As displayed on t following special File Nos. 128 - 2 Device 4 Device 5 Secondary Address Note: When using will be corrupted

### SUMMARY OF COMMANDS

@ COMMAND = Abbreviated disk commands.	
eg @S :NAME	Scratch File
@R :NEWNAME=OLDNAME	Rename File
@V	Validate Disk
@N :NAME	Renew Disk
@I	Initialize Drive
@N : Disk name, ID	Format disk in 20 seconds.
@B	3 minute disk backup.
@C	Selective fast file copier.
Note: Pressing RUN/STOP at any time will start the backup process.	
@P	Centronics interface.
@E	Exit centronics interface.
Note: Always exit centronics before carrying on with other work.	
@H	Help menu.
@Q	Quit cartridge.
\$	Load and display directory to screen only.
@	Disk status.
/NAME	Load to Basic.
%NAME	Load to file address.
^NAME	Load to Basic and Run.
<NAME	Save.
E	Change default drive from 8 to 9.
SYS 56904.	Restart cartridge.
SPACE BAR	Pause directory listing.

The reset switch software and does screen memory. To S033C hold down t An "OLD" feature this will restore Note: After using the computer off

The device number physically or by with the drive at switch the default 8 and 9. This will be used with the sec

Quickdisc+ will w

The cartridge save the RAM behind th can be loaded to ROM. The cartrid of the system ROM A cure for the we this can be used

### FUNCTION KEYS

The function keys have been programmed for the following commands...

F1	LIST
F3	RUN
F5	LOAD"0:*" 8.1
F7	DISPLAY DIRECTORY

Produce